Features


- 1-channel
- · AC version
- Working voltage 26 V at 10 μA
- Series resistance max. 327 Ω
- Fuse rating 50 mA
- · DIN rail mounting

Function

The Zener Barrier prevents the transfer of unacceptably high energy from the safe area into the hazardous area.

The zener diodes in the Zener Barrier are connected in the reverse direction. The breakdown voltage of the diodes is not exceeded in normal operation. If this voltage is exceeded, due to a fault in the safe area, the diodes start to conduct, causing the fuse to blow. The Zener Barrier has alternating polarities, i. e. interconnected zener diodes are employed and one side is grounded. The Zener Barrier can be used for both alternating voltage signals and direct voltage signals.


Assembly








Connection





Div. 2

Refer to "General Notes Relating to Pepperl+Fuchs Product Information

Release date 2020-01-08 08:50 Date of issue 2020-01-08 071857_eng.xml

AC version

General specifications

Electrical specifications

Type